

## Multi Camera Keypad

- Expands Joystick and Universal RCP up to 96 cameras
- Control up to 255 video matrix input selection
- Any of the 96 cameras assignable to up to 255 channel numbers
- Last 8 channel selection recall
- 4 definable mixer/stream button allocation
- Standalone operation or multi-operator with up to 4 joystick and 4 Universal RCP driving a single data line



The Camera Corps Multi Camera Keypad Control Unit provides a method of increasing the number of cameras/remote heads that can be controlled from either the Joystick Control unit, or the Universal RCP

The unit can be used in a simple 'standalone' mode with the Joystick or Universal RCP , to simply expand the number of cameras/remote heads being controlled. (Up to 96).

It can also be used with the Multi Camera Combiner unit to allow up to four Joystick operators and up to four RCP engineers to control the 96 cameras and Pan & Tilt Heads simultaneously using just a single data line.

An output is provided to drive many different types of Video Matrix to enable the operators monitor to follow the camera selection at any of the eight operator positions .

Although the number of cameras being controlled is limited to 96, the unit can select up to 255 channel numbers and Video Matrix select numbers to enable the system to fit in easily with the camera allocation on video matrices with up to 256 inputs.

# Speciality Camera Systems

